

## Necessary Keypad and SmartCard to store device settings

	VF1000 MC6000/7000	CDA3000 Standard	CDA3000 PLC	CDA3000 HF	CDD3000 CDD3000, HF CDS4000 CTC3000	CDB3000 CDE3000
<b>KP100</b> (A021.V00.0)	SC (Old) SC					
<b>KP200</b> (0840.0000) up to SW-V1.05 and without SW- label		SC (Old)	*)	SC (Old)	SC (Old) <sup>1)</sup>	*)
<b>KP200</b> (0840.0000) from SW-V1.10 (from KW44/2002)		SC (Old) SC	*)	SC (Old) SC	SC (Old) <sup>1)</sup> SC <sup>1)</sup>	*)
<b>KP200-XL</b> (0840.0010.0) <b>KP200-XL, R</b> (0840.0020.0)		SC (Old) SC SC-XL	SC (Old) SC SC-XL	SC (Old) SC SC-XL	SC (Old) <sup>1)</sup> SC <sup>1)</sup> SC-XL <sup>1)</sup>	SC-XL

\*) With this combination it is not possible to store device setting via SMARTCARD.  
Only setting/display of parameters is possible.

<sup>1)</sup> Only storing of parameters for speed-controlled operation on the SmartCard is possible.  
Parameters for positioning resp. iMotion process program will not be stored.

**SC (Old)**  
Old product up to KW44/2002  
A028.V01.0, Lust-imprint  
A028.V04.0, without imprint

Memory card with 2 kB

**SC**  
Product from KW44/2002  
replaces SC (Old)  
A028.V01.1, Lust-imprint  
A028.V04.1, without imprint

Memory card with 2 kB

**SC-XL**  
A028.V11.0, without imprint

Memory card with 16 kB